

How to make P-ROM at the **GALEP**

In case of 4M type ROM(AM27C4096 or HN27C4096AG)

Please connect **GALEP** and personal computer .

Please start the GALEP program.

1) Action Select device

Device type : EPROM
Manufactuer : AMD or HITACHI
Name : AM27C4096 or HN27C4096G
Please select OK and next.

2) Edit Option

File offset : 080000
Please select OK and next.

3) File Load File

File type(T) : Intel hex (HEX)
Drive(V) : Select drive in the system data
Folder(F) : Select folder in the system data
File name(N) : AVPX4 * * * .HEX (* * * : Ver. No.)
Please select OK and next.

4) Please set P-ROM in the GALEP.

5) Action Program

Please select OK .